

# MAGEWELL

## Pro Convert for NDI to AIO Module Technical Specifications

Copyright (c) 2011–2024 [Nanjing Magewell Electronics Co., Ltd.](#) All rights reserved.

Specifications are based on current hardware, firmware and software revisions, and are subject to change without notice.

HDMI, the HDMI logo and High-Definition Multimedia interface are trademarks or registered trademarks of HDMI Licensing LLC. NDI® is trademark or registered trademark of Vizrt Group.

Revised on 15/03/2024

### Interfaces

- 1\* RJ45 1000Mbps Ethernet port
- 1\* USB Type-C port for configuration
- 1\* SDI output port
- 1\* HDMI 1.4 output port
- 1\* Modator interface for connecting to Modator 2U (hot-swappable)

### Decoding Features

- Decode up to 2Kp60 streams of Full NDI®, NDI®|HX, NDI®|HX2, NDI®|HX3, RTSP, HTTP, HLS, RTMP Pull/Push, MPEG-TS over UDP/SRT/RTP, TVU protocols
- Simultaneously decode and output HDMI and SDI signals
- Decode H.264/H.265 video
- Decode AAC/MP3 audio
- Supports NDI® 6.0

### HDMI Output Features

- Max. output: 1920x1080p60
- Supports YUV BT.601/709 signals
- Supports 48KHz 8-channel audio output

### SDI Output Features

- Max. output: 1920x1080p60. Supported output formats are:
  - 1920x1080p 23.98/24/25/29.97/30/50/59.94/60
  - 1920x1080i 50/59.94/60
  - 1280x720p 24/25/29.97/30/50/59.94/60
  - 720x576p50
  - 720x576i50
  - 720x480i59.94
- Supports YUV BT.601/709 signals
- Supports 48KHz 8-channel audio output
- Supports SD (ST 259)/HD (ST 292)/3Ga (ST 425)/3Gb (ST 425)/3Gb-DL (ST 425)/3Gb-DS (ST 425) standards
- Output 3G-SDI signal with a transmitted distance greater than 150m

### Web UI

- Register with Magewell Control Hub for remote centralized management
- Supports configuring and managing via Web UI
- Provides comprehensive information regarding the device and decoded signals in real-time
- Allow to configure how a signal is decoded and output, including OSD settings, deinterlacing, resolutions, audio gain, sample rate, and channel mapping, as well as the network connection
- Supports updating firmware
- Supports USB RNDIS/ECM
- Supports IE/Edge/Firefox/Chrome/Safari/Opera web browsers
- Provides HTTP APIs

## LED Indicators

- Decode status indicator
  - On: decoding
  - Blinks: decoding error
  - Off: source unselected

## Physical Specifications

- Form factor: 184.4mm (L) x 30.0mm (W) x 81.5mm (H)
- Weight: ≈300g

## Power Consumption

- Max power consumption: 5.2W

## Working Environment

- Operating temperature: -10 to 45 deg C
- Storage temperature: -20 to 70 deg C
- Relative humidity: 5% to 90% non-condensing